



Anybus X-gateway - DeviceNet Scanner - POWERLINK Device

The Anybus X-gateway allows you to seamlessly inter-connect PLC control systems and their connected devices between DeviceNet and POWERLINK networks.

FAST COPYING OF I/O DATA

The X-gateways primary function is with the fast transfer of cyclic I/O data between the two networks. This offloads your PLC from working with additional calculations. The gateway acts as a Master on the DeviceNet network and a Slave/Device on the POWERLINK network. The data transmission is completely transparent with a maximum data capacity of 254 bytes in each direction.

EASY CONFIGURATION - NO PROGRAMMING REQUIRED!

The connection between the two networks is quickly set up in the Anybus Configuration Manager software, included with the X-gateway. No programming skills are needed to set up the X-gateway. As factory default the X-gateways have a pre-defined I/O size of 20 bytes I/O.



Features and benefits

- Fast copying of cyclic I/O data between the two networks (10-15 ms)
- Proven and tested with all PLC manufacturers
- Powerful Scanner/Master interface eliminates the need for a PLC controller on the DeviceNet network
- Supports up to a maximum of 512 bytes of PDO + SDO Input and Output data in each direction
- Supports up to a maximum of 254 bytes of PDO Input and Output data in each direction
- Fast, dynamic transfer of fieldbus data to e.g. SCADA/HMI/Enterprise level systems based on Microsoft Windows, via the included Anybus OPC server
- Optional control status information added to I/O data for diagnostic purposes
- Robust stand-alone housing for use in harsh industrial environments
- Global free technical support and consultancy

DeviceNet Scanner/Master features

An Anybus X-gateway with an integrated DeviceNet Scanner interface can be used when there is no existing DeviceNet controlling PLC.

- DeviceNet CONFORMANCE TESTED™ by ODVA
- DeviceNet Specification version: Communications Adapter profile 12
- Supports up to 63 DeviceNet Adapter/Slaves
- Max. 512 bytes of Input and 512 bytes of Output data
- Optional Live List of the active status of the connected adapters
- DeviceNet baudrate 125, 250, 500 kbit/s
- Supports I/O Slave messaging: Bit strobe, Polling, Cyclic and COS
- Node address setting via DIP switches

- 1x 5-pin, 5.08 Phoenix plug connector

POWERLINK Device/Slave interface

POWERLINK Device/Slave settings can be made either via the built-in web interface, or by importing the provided .XDD file into engineering tool of the controlling PLC.

- Max 254 bytes of Input and 254 bytes of Output data
- Baud rate 100 Mbit/s Isochronous
- Supports ring redundancy
- POWERLINK uplink configuration via .XDD file
- Dual port hub
- Multiplexing
- Poll Response Chaining
- Supports segmented SDO transfer
- Dual RJ-45 ports available simultaneously

TECHNICAL SPECIFICATIONS

Dimensions (L•W•H)	114 x 44 x 127mm or 4,49 x 1,73 x 5,00"
Weight	400g or 0,880 lbs
Operating temperature	-25 to +65 °C or -13 to +149 °F
Storage temperature	-40 to +85 °C or -40 to +185 °F
Power supply	24 VDC +/- 20% via 2-pole 5.08 mm Phoenix pluggable screw connector
Current consumption	max. 400mA (Typical 200mA)
Enclosure material	Aluminium and plastic
Installation position	Vertical / Flat*
Galvanic isolation	YES, on both BUS/Ethernet side
Mechanical rating	IP20, NEMA rating 1
Mounting	DIN-rail (EN 50022 standard)
I/O configuration	via USB port with Anybus Configuration Manager software
Certifications	CE, CULUS, RoHS

File	Version	Size	Read online
------	---------	------	-------------

Ordering information

Order Code	AB7522
Included components	Gateway Quick start documentation

USB configuration cable
Resource CD with DeviceNet master configuration software
Power supply **not** included

Configuration software is available for download

3 year guarantee. For purchasing instructions and terms and conditions, see: [How to buy](#).

Copyright © 2020 HMS Industrial Networks - All rights reserved.